



Product Service

Compliance Document

No. D 118897 0024 Rev. 00

Holder of Certificate: **Zhejiang Hyxi Technology Co., Ltd.**
9-10F, Building 3, Jiuyao Commercial Center
Zhuantang Street
Xihu District
310008 Hangzhou, Zhejiang
PEOPLE'S REPUBLIC OF CHINA

Product: **Converter**
Single Phase Hybrid Inverter

Model(s): **HYX-H3K-HS, HYX-H3K6-HS, HYX-H4K-HS,
HYX-H4K6-HS, HYX-H5K-HS, HYX-H6K-HS,
HYX-H8K-HS**


Parameters: See next pages.

Tested according to: EN 50549-1:2019
Ordinance No. 73/2020

This Compliance document confirms the compliance with the listed standards on a voluntary basis. It refers only to the sample submitted for testing and certification and does not certify the quality or safety of the serial products. For details see: www.tuvsud.com/ps-cert

Test report no.: 5040924020805-00

Date, 2024-11-21


(Zhengdong Ma)



Product Service

Compliance Document

No. D 118897 0024 Rev. 00

Models	HYX-H3K-HS		HYX-H3K6-HS	HYX-H4K-HS
PV Input Parameters				
Max. Input Voltage	DC 600 V			
MPPT Voltage Range	DC 80 V, ..., 560 V			
Max. Current per MPPT	DC 2*16 A			
Isc PV(absolute max.)	DC 2*24 A			
Battery Input Port Parameters				
Battery Type:	Lithium-ion			
Battery Voltage Range:	DC 80 V, ..., 490 V			
Max. Charge/Discharge Current:	DC 35 A			
On-grid(AC Input/Output) Parameters				
Rated Grid Voltage:	1/N/PE AC 230 V			
Rated Grid Frequency:	50 Hz			
Rated Output Power:	3000 W	3600 W	4000 W	
Max. Continuous current:	AC 15 A	AC 18 A	AC 20 A	
Max. Continuous Apparent Power:	3300 VA	4000 VA	4400 VA	
Power Factor	-0.8, ..., 1, ..., +0.8			

Models	HYX-H4K6-HS	HYX-H5K-HS	HYX-H6K-HS
PV Input Parameters			
Max. Input Voltage	DC 600 V		
MPPT Voltage Range	DC 80 V, ..., 560 V		
Max. Current per MPPT	DC 2*16 A		
Isc PV(absolute max.)	DC 2*24 A		
Battery Input Port Parameters			
Battery Type:	Lithium-ion		
Battery Voltage Range:	DC 80 V, ..., 490 V		
Max. Charge/Discharge Current:	DC 35 A		
On-grid(AC Input/Output) Parameters			
Rated Grid Voltage:	1/N/PE AC 230 V		
Rated Grid Frequency:	50 Hz		
Rated Output Power:	4600 W	5000 W	6000 W
Max. Continuous current:	AC 23 A	AC 25 A	AC 30 A
Max. Continuous Apparent Power:	5060 VA	5500 VA	6600 VA
Power Factor	-0.8, ..., 1, ..., +0.8		



Product Service

Compliance Document

No. D 118897 0024 Rev. 00

Models	HYX-H8K-HS
PV Input Parameters	
Max. Input Voltage	DC 600 V
MPPT Voltage Range	DC 80 V, ..., 560 V
Max. Current per MPPT	DC 2*16 A
Isc PV(absolute max.)	DC 2*24 A
Battery Input Port Parameters	
Battery Type:	Lithium-ion
Battery Voltage Range:	DC 80 V, ..., 490 V
Max. Charge/Discharge Current:	DC 35 A
On-grid(AC Input/Output) Parameters	
Rated Grid Voltage:	1/N/PE AC 230 V
Rated Grid Frequency:	50 Hz
Rated Output Power:	8000 W
Max. Continuous current:	AC 40 A
Max. Continuous Apparent Power:	8800 VA
Power Factor	-0.8, ..., 1, ..., +0.8



Compliance Document

No. D 118897 0024 Rev. 00

Interface protection settings and power controls in inverter (based on EN 50549-1:2019 with national deviation of Portugal according to Ordinance No. 73/2020)					
Clause(s) / subclause(s) of this EN	Ref	Parameter	Typical value range	Value default	
4.3.2 Interface switch	n.a.	Single fault tolerance for interface switch required	yes no	yes	
4.4.2 Operating frequency range	A,B	47.0 – 47.5 Hz Duration	0 – 20 s	10 s	
	A,B	47.5 – 48.5 Hz Duration	30 – 90 min	30 min	
	A,B	48.5 – 49.0 Hz Duration	30 – 90 min	30 min	
	A,B	49.0 – 51.0 Hz Duration	not configurable	unlimited	
	A,B	51.0 – 51.5 Hz Duration	30 – 90 min	30 min	
	A,B	51.5 – 52 Hz Duration	0 – 15 min	1 min	
4.4.3 Minimal requirement for active power delivery at underfrequency	A,B	Reduction threshold	49 Hz – 49.5 Hz	No reduction	
	A,B	Maximum reduction rate	2 – 10 % P _M /Hz	N/A	
4.4.4 Continuous operating voltage range	n.a.	Upper limit	not configurable	110%Un	
	n.a.	Lower limit	not configurable	85%Un	
4.5.2 Rate of change of frequency (ROCOF) immunity	A,B	ROCOF withstand capability (defined with a sliding measurement window of 500 ms)	not defined	2 Hz/s	
		non-synchronous generating technology:		2 Hz/s	
		synchronous generating technology:		N/A	
4.5.3.2 Generating plant with non- synchronous generating technology	B	Maximum power resumption time	not defined	1s	
	B	Voltage-Time-Diagram	see Figure 6	Time [s]	U [p.u.]
				0	0.05
				0.25	0.05
4.5.3.3 Generating plant with synchronous generating technology	B	Maximum power resumption time	not defined	N/A	
	B	Voltage-Time-Diagram (N/A)	see Figure 7 (N/A)	Time [s]	U [p.u.]
				-	-
				-	-
				-	-
				-	-
				-	-
4.5.4 Over-voltage ride through (OVRT)	n.a.	Voltage-Time-Diagram	not configurable	Time [s]	U [p.u.]
				0.0	1.25
				0.1	1.25
				0.1	1.20
				5.0	1.20
				5.0	1.15
				60.0	1.15
				60.0	1.10
4.6.1 Power response to overfrequency	A,B	Threshold frequency f ₁	50.2 Hz – 52 Hz	50.2 Hz	
	A,B	Droop	2 % – 12 %	5 %	



Compliance Document

No. D 118897 0024 Rev. 00

	A,B	Power reference	$P_M P_{max}$	P_{max} for EESS
	n.a.	Intentional delay	0 – 2 s	0 s
	n.a.	Deactivation threshold f_{stop}	50,0 Hz – f_1	50.1 Hz
	n.a.	Deactivation time t_{stop}	0 – 600 s	30 s
	A	Acceptance of staged disconnection	yes no	yes
4.6.2 Power response to underfrequency	n.a.	Threshold frequency f_1	49.8 Hz – 46 Hz	49.8 Hz
	n.a.	Droop	2 – 12 %	5 %
	n.a.	Power reference	$P_M P_{max}$	P_{max}
	n.a.	Intentional delay	0 – 2 s	0 s
4.7.2.2 Capabilities	B	Active factor range overexcited	0.9 – 1	1
	B	Active factor range underexcited	0.9 – 1	1
4.7.2.3 Control modes	n.a.	Enabled control mode	Q setpoint Q(U) cos φ setpoint cos φ (P)	Q setpoint
4.7.2.3.2 Setpoint control modes	n.a.	Q setpoint and excitation	0 – 48.4 % P_D	0
	n.a.	cos φ setpoint and excitation	1 – 0.9	1
4.7.2.3.3 Voltage related control modes	n.a.	Characteristic curve	-	-
	n.a.	Time constant	3 s – 60 s	10 s
	n.a.	Min cos φ	0.0 – 1	1
	n.a.	Lock in power	0 % – 20 %	20 %
	n.a.	Lock out power	0 % – 20 %	5 %
4.7.2.3.4 Power related control mode	n.a.	Characteristic curve	-	disable
4.7.4.2.2 Zero current mode for converter connected generating technology	n.a.	Enabling	enable disable	disable
	n.a.	Static voltage range overvoltage	100 % U_n – 120 % U_n	115 % U_n
	n.a.	Static voltage range undervoltage	20 % U_n – 100 % U_n	85 % U_n
4.9.2 Requirements on voltage and frequency protection	n.a.	Threshold for protection as dedicated device [in A or kW, kVA]	16 A – 250 kVA	Interface protection integrated
	B	Undervoltage threshold stage 1	0.2 U_n – 1 U_n	0.85 U_n
	B	Undervoltage operate time stage 1	0.1 s – 100 s	3 s
	B	Undervoltage threshold stage 2	0.2 U_n – 1 U_n	0.4 U_n
	B	Undervoltage operate time stage 2	0.1 s – 5 s	1.5 s
	B	Overvoltage threshold stage 1	1.0 U_n – 1.2 U_n	1.15 U_n
	B	Overvoltage operate time stage 1	0.1 s – 100 s	1.5 s
	B	Overvoltage threshold stage 2	1.0 U_n – 1.3 U_n	1.25 U_n
	B	Overvoltage operate time stage 2	0.1 s – 5 s	0.1 s
	B	Overvoltage threshold 10 min mean protection	1.0 U_n – 1.15 U_n	1.10 U_n



Product Service

Compliance Document

No. D 118897 0024 Rev. 00

	B	Underfrequency threshold stage 1	47.0 Hz – 50.0 Hz	47.50 Hz
	B	Underfrequency operate time stage 1	0.1 s – 100 s	5.0 s
	B	Underfrequency threshold stage 2	47.0 Hz – 50.0 Hz	47.00 Hz
	B	Underfrequency operate time stage 2	0.1 s – 5 s	0.1 s
	B	Overfrequency threshold stage 1	50.0 Hz – 52.0 Hz	51.50 Hz
	B	Overfrequency operate time stage 1	0.1 s – 100 s	5.0 s
	B	Overfrequency threshold stage 2	50.0 Hz – 52.0 Hz	52.00 Hz
	B	Overfrequency operate time stage 2	0.1 s – 5 s	0.1s
4.10.2 Automatic reconnection after tripping	B	Lower frequency	47.0 Hz – 50.0 Hz	47.5 Hz
	B	Upper frequency	50.0 Hz – 52.0 Hz	51.5 Hz
	B	Lower voltage	50 % U_n – 100 % U_n	85% U_n
	B	Upper voltage	100 % U_n – 120 % U_n	110 % U_n
	B	Observation time	10 s – 600 s	60s
	B	Active power increase gradient	6 % – 3000 %/min	10 %/min
4.10.3 Starting to generate electrical power	A,B	Lower frequency	47.0 Hz – 50.0 Hz	47.5 Hz
	A,B	Upper frequency	50.0 Hz – 52.0 Hz	51.5 Hz
	A,B	Lower voltage	50 % – 100 % U_n	85% U_n
	A,B	Upper voltage	100 % – 120 % U_n	110 % U_n
	A,B	Observation time	10 s – 600 s	60s
	A,B	Active power increase gradient	6 % – 3000 %/min	Disable
4.11.1 Ceasing active power	A,B	Remote operation of the logic interface	yes no	Can be achieved by PGU. (Logic interface shall be specified by DNO)
4.11.2 Reduction of active power on set point	B	Remote operation NOTE: If yes further definition is provided by the DSO	yes no	Can be achieved by PGU. (Definition shall be specified by DNO)
4.12 Remote information exchange	B	Remote information exchange required NOTE: If yes further definition is provided by the DSO	yes no	N/A
The Column Ref specifies if a parameter is relevant for COMMISSION REGULATION 2016/631 and for what type of generating module the parameter is relevant. If n.a. is set, this parameter is: not applicable for 2016/631, but is introduced into EN50549-1 for local DSO network management reasons and is not considered as cross border issues. Unauthorised access to factory safety parameters setting and software should be prohibited. A reset to the factory safety parameters requires retesting and verification in conjunction with the end-use system.				